



Client:

Project:

Type:

Order Code:

Quantity:

Canvas is a simple, yet powerful touch screen DMX controller designed for permanent installation. It's easy to navigate interface will walk you through the initial setup, give you up to 30 automatic presets, and then allows you to modify any aspect as needed from there. It features two DMX universes, two 0-10V lines, 8 dry contact triggers, and Aria wireless DMX built in.

SPECIFICATIONS

DMX Output	1024 channels, 2 universes
0-10V Output	2 outputs, sink
Interface	3.5" TFT touch panel
Dry Contact Input Triggers	8
Internal Clock	RTC, user adjusted
Operating Voltage	110-277VAC, 50/60 Hz
User Programmable Elements	80 static presets, 20 moving program presets (max 80 steps), 60 timer controlled events
Mobile Application	Canvas app available for iOS and Android for preset trigger and dimmer adjustment
Mounting	3 gang north american wall box
Wireless DMX	Aria transmitter built-in, transmits universe one (512 channels maximum)
Finish	White, almond, gray, and black face plates included
Material	Polycarbonate
Ambient Operating Temperature	14° F to 122° F (-10° C to 50° C)
IP Rating	IP20, dry location
Program and Firmware Storage	via Included micro SD card, 4 GB minimum
Fixture Connectors	Push lock terminal blocks for all inputs and outputs
Warranty	2 Years, limited
Weight	TBA
Dimensions	L: 6.3" (includes faceplate) W: 4.7" D: 2.36" (160 x 119 x 60mm)

Certifications



ORDER CODES

CAN100: Canvas Lighting Controller

White, almond, gray, and black face plates included

DIMENSIONS

